



2 4G LED Dimming Controller









Main Characteristics


RF Dimming Remote Control

Remote Option: Dimmina

3Vdc (Battery CR2032) Working Voltage:

Wireless Frequency: 2 4GHz Visual Distance: 20m Working Temperature: -30 ~55

Package Size: L150×W46×H18(mm) Weight(G.W.): 80a



Input Voltage: 5~2/JVdc

3A × 4CH Max. 12A Max Current Load: Max Output Power: 60W/144W/288W(5V/12V/24V)

Working Temperature:

L127×W35×H24(mm) Package Size:

Weight(G.W.): 60g

F4-5A CV Receiver

5~24Vdc Input Voltage:

Max Current Load: 5A × 4CH Max. 20A


Max Output Power: 100W/240W/480W(5V/12V/24V)


Working Temperature: -30 ~55

Package Size: L178×W48×H33(mm)

Weight(G.W.): 150a

Note: Receiver is sold separately.





F4-CC CC Receiver

Input Voltage: 12~48Vdc 3~46Vdc Output Voltage:


CC 350/700/1050mA×4CH Output Current: Output Power: 1 05W~48 3W×4CH Max 193 2W


-30 ~55 Working Temperature:


L178×W48×H33(mm) Package Size:


Weight(G.W.): 165g

Dimensions










www.ltechonline.com






Operating Instruction for Remote:



Match/Clear code between remotes



Press the bottom two keys of B simultaneously (about 6 seconds) until the indicator light keeps on, deactivated matching successfully.

Match/Clear code between remote and receiver

Α R

Match code:

Method 1 ·

Step 1. Power on the receiver, and complete step 2 in 10 seconds.

Step 2. Long press (') on the remote, the lamps

flicker several times, the buzzer beep once, match successfully.

Clear code:

Method 1 ·

Power on and off the receiver continuously for 5 times. If the buzzer long beep and lamps flicker twice, deactivate the matching successfully.



Method 2:

Step 1. Short press the ID learning button on the receiver, the buzzer beep once.

Step 2. Long press () on the remote, the lamps flicker several times, the buzzer beep once, match successfully.

Method 2:

Long press "ID learning button" on receiver for 5 seconds, If the lamps flicker twice, deactivate the matching successfully.




Wiring Diagram:



F1



ID learning button





150W LED Mining Light www.ltechonline.com